



Introduction -

I-87042W offers 16 channels for digital input and 16 channels for digital output.Each of which features Photo-couple isolation.I-87042W supports sink type output with short-circuits protection. There are option for Poweron value and safe value for your consideration. About Input, you can chose sink type or source type input by wire connection. All channels are able to be used as 16-bit counter. I-87042W also has 32 LED indicators for channel status. 4 kV ESD protection and 3750 Vpc intra-module isolation are standard.

System Specifications -

Communication		
Interface	RS-485	
Format	N, 8, 1	
Baud Rate	1200 ~ 115200 bps	
Protocol	DCON	
Dual Watchdog	Yes, Module (1.6 Seconds), Communication (Programmable	
Safe Value (When Host Fail or Communication Fail)	Yes	
Power-on Preset Value	Yes	
LED Indicator/Display		
System LED Indicator	1 LED as Power/Communication Indicator	
I/O LED Indicator	32 LEDs as Digital Input and Output Indicators	
Isolation		
Intra-Module Isolation, Field-to-Logic	3750 Vpc	
EMS Protection		
ECD (IEC 61000 4 3)	4 kV Contact for Each Terminal	
ESD (IEC 61000-4-2)	±8 kV Air for Random Point	
Power		
Power Consumption	1.25 W ,+/- 5% For Hardware	
Mechanical		
Dimensions (W x L x H)	30 mm x 85 mm x 115 mm	
Environment		
Operating Temperature	-25 ~ +75°C	
Storage Temperature	-40 ~ +85°C	
Humidity	10 ~ 95% RH, Non-condensing	

Features

- Digital Input for Sink Type or Source Type
- Digital Outputs for Sink Type
- Power-on Value Setting
- Safe Value Setting
- Photocouple Isolation
- 4 kV ESD Protection
- 3750 Vpc Intra-module Isolation
- RoHS Compliance
- Wide Operating Temperature Range: -25°C ~ +75°C










Applications


- Industrial Automation
- Industrial Machinery
- Building Automation
- Food and Beverage Systems
- Semiconductor Fabrication
- Control Systems


I/O Specifications -

Digital Input		
Channels	16	
Туре	One common for all Inputs	
Sink /Source (NPN /PNP)	Sink, Source	
On Voltage Level	+3.5 Vpc ~ 30 Vpc	
Off Voltage Level	+1 V _{DC} Max.	
Input Impedance	3 ΚΩ	
Counter (100 Hz, 16-bit)	Yes	
Channel to Channel Isolation	Yes	
Digital Output		
Channels	16	
Туре	Open Collector	
Sink /Source (NPN /PNP)	Sink	
Load Voltage	+5 Vpc ~ +30 Vpc	
Max. Load Current	100 mA/Channel	
Overload Protection	Yes	
Short Circuit Protection	-	
Power-on Value	Yes	
Safe Value	Yes	

Dimensions (Units: mm)








Top View

Wire Connections _




Input Type	ON State LED ON Readback as 1	OFF State LED OFF Readback as 0	
	Relay ON	Relay OFF	
Relay Contact (Sink)	- Elay Close DIx	- I DI.COM/DO.GND DIx	
	Voltage > 3.5 V	Voltage < 1 V	
(C:-L)	Logic Level Low Logic Power DI.COM/DO.GND DIX	Logic Power DI.COM/DO.GND DIX	
	Open Collector ON	Open Collector OFF	
NPN Output (Sink)	DI.COM/DO.GND	DI.COM/DO.GND	
PNP Output (Sink)	Open Collector ON	Open Collector OFF	
	ON THE DECOM/DO.GND DIX	OFF THE DI.COM/DO.GND DIX	


Input Type	ON State LED ON Readback as 1	OFF State LED OFF Readback as 0
	Relay ON	Relay OFF
Relay Contact (Source)	+ DI.COM/DO.PWR - Relay Close DIx	+ □ □ □ DI.COM/DO.PWR □ □ DIX
	Voltage > 3.5 V	Voltage < 1 V
TTL/CMOS Logic (Source)	Logic Power Logic Level Low DI.COM/DO.PWR DIX	Logic Level High
	Open Collector ON	Open Collector OFF
NPN Output (Source)	ON LIL ON DIX	OFF LINE DI.COM/DO.PWR
PNP Output (Source)	Open Collector ON	Open Collector OFF
	DI.COM/DO.PWR	OFF- X × □ □ DI.COM/DO.PWR DIx

Output Type	ON State LED ON Readback as 1	OFF State LED OFF Readback as 0	
	Relay ON	Relay OFF	
Drive Relay	DI.COM/DO.PWR DOX DO.GND	DI.COM/DO.PWR DOX DO.GND	
Resistance Load	DI.COM/DO.PWR DOX DO.GND	DI.COM/DO.PWR DOX DO.GND	

■ Internal I/O Structure _



Pin Assignments .



Pin Assignment	Terminal	0	No.	Pin Assignment
DI.COM/DO.PWR	19		37	DI.COM/DO.PWR
DO.GND	18		36	
DO.GND	17	•		DO.GND
DI_15	16	•	35	DO_15
DI_14	15	•	34	DO_14
DI_13	14	•	33	DO_13
DI_12	13	•	32	DO_12
DI_11	12	•	31	DO_11
DI 10	11	•	30	DO_10
DI 9	10	•	29	DO_9
DI 8	09	•	28	DO_8
DI 7	08	•	27	DO_7
DI 6	07	•	26	DO_6
DI 5	06	•	25	DO_5
DI 4	05	•	24	DO_4
DI 3	04		23	DO_3
DI 2	03	•	22	DO_2
DI_2 DI 1	02	•	21	DO_1
DI_I DI 0	02	•	20	DO_0
51_0	01	0		-pin Male b Connector

Ordering Information

I-87042W-G CR

16-channel Isolated Digital Input & 16-channel Isolated Digital Output Module (Gray Cover) (RoHS)

Accessories -

DN-8K16P16R	16 channel input terminals and 16 channel relay outputs board
DN-37-A	I/O Connector Block with DIN-Rail Moun ting and 37-pin D-sub Connector (pitch:5.08 mm)
DN-37-381-A	I/O Connector Block with DIN-Rail Moun ting and 37-pin D-sub Connector (pitch:3.81 mm)
CA-3705A	Male-Female D-sub Cable 0.5 M
CA-3710A	Male-Female D-Sub Cable 1M

