



#### **Features**

- Built-in Web Server for IF-THEN-ELSE rule setting
- Built-in IF-THEN-ELSE rule enigne for logic operation
- No more programming. Just click and get done!
- Support IO, Counter, Timer, Email operations
- Modbus/TCP Protocol for SCADA Software Seamless Integration
- IEEE 802.3af-compliant Power over Ethernet (PoE)
- 10/100 Base-TX Ethernet
- AI: 3 (mV, V, mA)
- DO: 3 (Power Relay, Form A)
- DI: 6 (Wet Contact)











#### Introduction.

WISE (Web Inside, Smart Engine) is a product series developed by ICP DAS that functions as control units for use in remote logic control and monitoring in various industrial applications. WISE offers a user-friendly and intuitive web site interface that allows users to implement IF-THEN-ELSE control logic on controllers just a few clicks away; no programming is required. With its powerful and easy-to-use features, it will minimize the learning curve, shorten time to market and dramatically reduce the labor and cost spent on system development.

WISE-7102 follows IEEE 802.3af-compliant (classification, Class 1) Power over Ethernet (PoE) specification. It allows receiving power from PoE enabled network by Ethernet pairs (Category 5 Ethernet cable). This feature provides greater flexibility and higher efficiency therefore simplifying systems design, saving space, reducing cables and eliminating the requirement for dedicated electrical outlets. Meanwhile, in case under a non-PoE environment, WISE-7102 will still be able to receive power from auxiliary power sources like AC adapters or battery, etc.

This multi-function module WISE-7102 supports Modbus/TCP protocol to make seamless integration with SCADA software available. It features 3-channel analog inputs, 6-channel digital inputs and 3-channel Power Relay outputs. Each analog input channel provides 240 Vrms high over voltage protection.

### Applications -

Building Automation, Factory Automation, Machine Automation, Remote Maintenance, Remote System Specifications \_\_\_\_\_ Diagnosis, Testing Equipment, etc.

#### I/O Specifications \_

Analog Input			
Input Channels		3 (Differential)	
Input Type		+/-150mv, +/-500mv, +/-1 V, +/-5 V, +/-10 V	
(jumper selectable)		+/-20 mA, 0 ~ 20 mA, 4 ~ 20 mA	
Resolution		16-bit	
Sampling Rate		10 Sample/Sec. (Total)	
Accuracy		+/-0.1%	
Zero Drift		+/-20 µV/°C	
Span Drift		+/-25 ppm/°C	
Overvoltage Protec	tion	240 Vrms	
Overcurrent Protec	tion	50 mA max. at 110 V <sub>DC</sub> /V <sub>AC</sub> max.	
Tonish Immedance	Voltage	2 ΜΩ	
Input Impedance	Current	125 Ω	
Common Mode Rej	ection	86 dB Min.	
Normal Mode Reject	ction	100 dB	
Individual Channel	Configuration	Yes	
Open Wire Detection	on	Yes, for 4 ~ 20 mA only	
Digital Input			
Channels		6	
Contact		Wet Contact	
Sink/Source (NPN/I	PNP)	Sink/Source	
On Voltage Level		+10 V <sub>DC</sub> ~ +50 V <sub>DC</sub>	
Off Voltage Level		+4 V <sub>DC</sub> Max.	
Input Impedance		10 KΩ, 0.5W	
	Channels	6	
Counters	Max. Counts	16-bit (65535)	
Counters	Max. Input Frequency	50 Hz	
	Min. Pulse Width	10 ms	
Overvoltage Protec	tion	+50 V <sub>DC</sub>	
Power Relay			
Channels		3	
Туре		Power Relay, Form A (SPST N.O.)	
Operating Voltage Range		250 V <sub>AC</sub> /30 V <sub>DC</sub>	
Max. Load Current		5.0A/channel at 25°C	
Operate Time		6 ms (Typical)	
Release Time		3 ms (Typical)	
		VDE: 5 A @ 250 V <sub>AC</sub> 30,000 ops (10 ops/minute) at 75°C.	
Electrical Life ( Res	istive load )	5 A @ 30 V <sub>DC</sub> 70,000 ops (10 ops/minute) at 75°C.	
Licercui Lire ( Nes	.oa.c .oud )	UI : 5 A @ 250 V <sub>AC</sub> /30 V <sub>DC</sub> 6,000 ops.	
		3 A @ 250 V <sub>AC</sub> /30 V <sub>DC</sub> 100,000 ops.	
Mechanical Life		20,000,000 ops. at no load (300 ops./minute).	
Intra-module Isolation, Field to Logic		3750 VDC	

System	
CPU	16-bit CPU
SRAM	512KB
Flash Memory	512KB
EEPROM	16KB
Watchdog	Yes
Communication	
PoE Ethernet Port	10/100 Base-TX and automatic MDI/ MDI-X
2-Way Isolation	
I/O	2500 VDC
EMS Protection	
ESD (IEC 61000-4-2)	4 kV Contact for each terminal and 8 kV Air for random point
EFT (IEC 61000-4-4)	+/-4 kV for Power
LED Indicators	
PoE Power	PoE On
L1	System Running
L2	Ethernet Link/Act
L3	Ethernet 10/100 M Speed
Power Requirements	
Reverse Polarity Protection	Yes
Powered from Terminal Block	Yes, 12 ~ 48 Vpc
Powered from PoE	Yes, IEEE 802.3af, Class1
Consumption	1.7W
Mechanical	
Dimensions (W x L x D)	72 mm x 123 mm x 35 mm
Installation	DIN-Rail or Wall mounting
Environment	
Operating Temperature	-25 °C ∼ +75 °C
Storage Temperature	-30 °C ~ +80 °C
Humidity	10 ~ 90% RH, non-condensing

# ■ Software Specifications \_\_\_\_\_

Functions	
Rule Configuration Website	Access Web server on WISE controllers to edit and upload logic rules through web browser.
36 IF-THEN-ELSE Logic Rules	3 IF conditions with AND or OR operators 3 THEN actions and 3 ELSE actions
48 Internal Registers	Hold temporary variables and read/write data via Modbus/TCP address.
12 Timers	Delay / Timing functions.
12 Emails	Send Email messages to pre-set Email receivers.
12 CGI Commands	Send pre-set CGI commands.
12 Recipes	Set up THEN/ELSE action groups.
8 P2P remote modules	Set up the connection information for the remote WISE modules.
Modbus/TCP Protocol	Real time control and monitoring I/O channels and system status of controllers via SCADA software.

	IF Conditions	
DI Channel	ON, OFF, ON to OFF, OFF to ON, Change	
AI Channel	(	
Internal Register	=, >, <, >=, <= (value)	
DI Counter	=, >, <, >=, <= (value), Change	
DO Counter	=, >, <, >=, <= (value), Change	
Timer	Timeout, Not Timeout	
P2P	DI, AI, DI counter, DO counter, IR	
Rule Status	Enable, Disable	



THEN / ELSE Actions		
DO Channel	ON, OFF, Pulse Output	
Internal Register	Change the value	
DI Counter	Reset	
DO Counter		
Timer	Start, Reset	
Email	Send	
CGI Commands	Sena	
Recipe	Execute	
P2P	DO(On/Off), AO, IR	
Rule Status	Enable, Disable	

# ■ Pin Assignments \_\_

Terminal No.	Pin Assignment
E1	RJ-45
01	Vin 0+
02	Vin 0-
03	Vin 1+
04	Vin 1-
05	Vin 2+
06	Vin 2-
07	N/A
08	(R)+Vs
09	(B)GND



Terminal No.	Pin Assignment
23	IN 5
22	IN 4
21	IN 3
20	IN 2
19	IN 1
18	IN 0
17	IN.COM
16	IN.COM
15	RL2 COM
14	RL2 NO
13	RL1 COM
12	RL1 NO
11	RL0 COM
10	RL0 NO


#### Wire Connections

#### Current Input Voltage Input JUMPER JUMPER Vin+ Vin-

Digital Input/	Readback as 1	Readback as 0
Counter	+10 ~ +50 VDC	OPEN or <4 VDC
Sink	DIX 10K	DIX 10K
	+10 ~ +50 V <sub>DC</sub>	OPEN or <4 VDC
Source	DIX 10K  To other DI.com  To other channels	DIX 10K
Power Relay	ON State	OFF State

Power Relay	Readback as 1	Readback as 0
Relay Output	RLx.COM Relay Close  AC/DO Relay Close  : To other channels	RLx.COM Relay Open Relay Open To other channels

# ■ Dimensions (Unit:mm) \_



## Ordering Information \_

WISE-7102 3-Channel Analog Inputs, 6-Channel Digital Inputs and 3-Channel Power Relay Outputs PoE Module (RoHS)

#### Accessories

	_ / 10000001100 _	
	GPSU06U-6	24V/0.25A, 6 W Power Supply
	MDR-20-24	24V/1A, 24 W Power Supply with DIN-Rail Mounting
	NS-205 CR	Unmanaged 5-Port Industrial Ethernet Switch (RoHS)
NS-205PSE CR Unmanaged 5-Port Industrial PoE Ethernet Switch (RoHS)		Unmanaged 5-Port Industrial PoE Ethernet Switch (RoHS)